


# NASA TECH BRIEF



NASA Tech Briefs are issued by the Technology Utilization Division to summarize specific technical innovations derived from the space program. Copies are available to the public from the Clearinghouse for Federal Scientific and Technical Information, Springfield, Virginia, 22151.

## Voltage Variable Oscillator Has High Phase Stability



**The problem:** Although frequency-modulated oscillators are available, their applications are restricted by certain operating limitations. In LC or reactance-tube oscillators relatively low levels of phase stability are normal, and in piezoelectric crystal oscillators, modulation is limited to a fraction of a percent of the center frequency.

**The solution:** A voltage variable oscillator using a low noise, phase stable amplifier with negative feedback, plus two (or more) series resonant LC circuits for high phase stability and optimum frequency deviation.

**How it's done:** The resonant part of the oscillator consists of two identical series resonant circuits, each consisting of an inductor (L) and a voltage variable capacitance ( $C_v$ ) loosely coupled by capacitor  $C_2$ . Since  $C_v$  is a voltage variable capacitance, the oscillator frequency can be varied by applying a modulating voltage. A low-pass filter section, consisting of  $C_1$ ,  $L_1$ , and  $C_2$ , is used to isolate the RF oscillator signal from the modulating signal. The filter load resistor R has a resistance much greater than the capacitive reactance of  $C_2$  at the oscillation frequency.

Amplifier negative feedback is accomplished by the network consisting of  $C_3$ ,  $D_1$ ,  $D_2$ , and  $D_3$ . A dc voltage proportional to the oscillator output voltage is developed across  $D_3$  and  $C_3$  and applied to the high-frequency point contact diodes  $D_1$  and  $D_2$ . If the amplifier output tends to increase, the higher output signal reduces the dynamic resistance of  $D_1$  and  $D_2$  and negative feedback to the amplifier increases to maintain a constant output signal level.

**Note:** Inquiries concerning this invention may be directed to:

Technology Utilization Officer  
Langley Research Center  
Langley Station  
Hampton, Virginia, 23365  
Reference: B65-10204

**Patent status:** NASA encourages the immediate commercial use of this invention. It is owned by NASA and inquiries about obtaining royalty-free rights for its commercial use may be made to NASA, Code AGP, Washington, D.C., 20546.

Source: Chase P. Hearn  
(Langley-123)

Category No. 01